

HMIX-622

# 1U RACK 8-INPUT STEREO MIXER

The HMIX-622 is designed for Commercial Audio applications where many microphone or line inputs are required. The Mic/Line section consists of 6 combo inputs (XLR + ¼" Jack) with level control, Mic/Line selector and Phantom power in case of condenser microphones. Channel 1 also has Priority function with adjustable threshold. The Aux section provides 2 stereo RCA inputs, also with independent level, and a stereo li line output with RCA connectors for recording or connecting to other devices. Finally, the master section has stereo output with balanced XLR connectors, mono output with ¼" jack connector, volume control and front stereo VU meter. The mixer accepts DC24V auxiliary power for emergency systems.



HMIX-622

# 1U RACK 8-INPUT STEREO MIXER

## PRODUCT DETAILS

### KEY FEATURES

6 Mic/Line inputs

+48V phantom power supply

Priority function (on channel 1) with adjustable threshold

2 Stereo Line Inputs

Stereo Balanced Outputs

Small size in 1 rack unit

DC24V auxiliary power input

### SPECIFICATIONS

<b>Mic/Line Inputs</b>	6x Balanced XLR / 1/4" Combo connectors
<b>Aux Inputs</b>	2x L+R RCA
<b>Outputs</b>	L+R male XLR, 1/4" Jack, L+R RCA (Line Out)
<b>Controls</b>	6x Mic/Line level, 2x Aux level, Treble (High), Bass (Low), Master
<b>Input Impedance</b>	3.3k Ohms (mic/line), 10k Ohms (aux)
<b>Mic Frequency Response</b>	20Hz - 18kHz
<b>Line Frequency Response</b>	14Hz - 20kHz
<b>Aux Frequency Response</b>	10Hz - 23kHz
<b>Mic Input Sensitivity</b>	-45dBV
<b>Aux/Line Input Sensitivity</b>	-10dBV
<b>Mic S/N Ratio</b>	55dB
<b>Aux/Line S/N Ratio</b>	60dB

HMIX-622

# 1U RACK 8-INPUT STEREO MIXER

<b>THD</b>	0.05%
<b>Power Supply</b>	100-240Vac 50/60Hz (IEC) or 24VDC (terminals)
<b>Fuse</b>	T1AL 250V (mains) or F500mA (24DC)
<b>Phantom Power</b>	+48V (switchable)
<b>Product Size (WxDxH)</b>	482 x 132 x 45 mm (18.9 x 5.2 x 1.7 in.)
<b>Product Weight</b>	1.7 kg (3.75 lbs.)
<b>Carton Size</b>	565 x 210 x 74 mm (22.2 x 8.3 x 2.9 in.)
<b>Carton Weight</b>	1.9 kg (4,19 lbs.)