


## DJM-S3 2-CHANNEL MIXER FOR SERATO DJ

Thanks to the built-in soundcard, this 2-channel mixer is Serato DJ enabled as soon as you unpack it. Featuring a highly durable Magvel crossfader, inherited from the DJM-900NXS2, the DJM-S3 delivers a smooth and accurate response. The scratch-friendly layout creates more room for you to be creative in the booth. No need to go easy, the DJM-S3 is built to withstand intense performances. And to bring even more creativity to your performances, you can connect the DDJ-SP1 controller and use its large Performance Pads for tactile control of many Serato DJ features, including its FX.



DJM-S3

# 2-CHANNEL MIXER FOR SERATO DJ

## PRODUCT DETAILS

### KEY FEATURES

Built-in sound card

Magvel Crossfader

Independent channel filters

High Quality sound

Flexible connectivity

Two headphone output

### SPECIFICATIONS

DVS control with Serato DJ

**Dimensions (WxHxD)** 230x108x320 mm

**Weight** 3 Kg

**Frequency range** 20 - 20000 Hz

**Sampling rate** 48 Hz

**A/D Converter** 24 bit

**D/A Converter** 24 bit

**S/N ratio** 94 dB (line)

**Distortion** < 0.005 % (line)

**Power supply** AC adaptor DC 12V

**Power consumption** 600 mA

**EQ/ISO** 3 band -8 ~ +6 dB

**Channels** 2

DJM-S3

## 2-CHANNEL MIXER FOR SERATO DJ

**Sound color FX**

Filter

**Inputs**

3 LINE (RCA), 2 PHONO (RCA), 1 MIC (1/4 inch TS Jack)

**USB**

1 USB B port

**Outputs**

1 MASTER (XLR), 1 MASTER (RCA), 2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)