

MCTRL300

LED DISPLAY CONTROLLER NOVASTAR MCTRL300

The MCTRL300 is an LED controller developed by Novastar that enables LED displays to be configured in a very short time.

The sending card is housed in a stable metal housing and supports 1 DVI input, 1 3.5 mm audio input and 2 Ethernet outputs. A single MCTRL300 supports input resolutions up to 1920×1200@60Hz. The MCTRL300 communicates with the PC via the USB Type-B port. Multiple MCTRL300 units can be cascaded via the UART port. In addition, the controller is equipped with a light sensor connector to which the Novastar NS060 can be connected for automatic brightness monitoring.

As a highly cost-effective controller, the MCTRL300 can be used primarily in rental and fixed installation applications, such as live events, security monitoring centres and various sports centres.



MCTRL300

LED DISPLAY CONTROLLER NOVASTAR MCTRL300

PRODUCT DETAILS

KEY FEATURES

Connection for light sensor

Up to 20 devices can be cascaded via UART control ports

PC communication via USB Type-B port

Pixel brightness and chroma calibration via NovaLCT software

1.3 million pixel loading capacity

Supports resolutions up to 1920x1200@60Hz, downward compatible

Custom resolutions supported: max width: 3840x600@60Hz, max height: 548x3840@60Hz

SPECIFICATIONS

1x SL-DVI input

1x TRS balanced 3.5mm audio input

2x Gigabit Ethernet outputs

2x UART control ports

1x Light sensor connector

LED indicators

Input voltage AC 100V-240V 50/60Hz

Rated power consumption 3W

Working temperature from -20°C to +60°C

Working humidity 0% RH-90% RH, non-condensing

Product sizes 204 x 160 x 48 mm (8.03 x 6.30 x 1.89)

Product weight 1.4 kg (3.8 lbs)