

SCENEMAKER 1232

12 FIXTURES X 32 CHANNELS DMX INTELLIGENT LIGHTING CONTROLLER

SCENEMAKER 1232 is a universal intelligent lighting controller.

It allows you to manage up to 12 fixtures composed of 32 channels each (384 channels in total), and up to 240 programmable scenes. 6 chases can contain up to 240 steps composed by the saved scenes (the steps) and in any order. Programs can be triggered by music, MIDI, automatically or manually. On the surface you will find various programming tools such as 16 universal channel sliders, quick access scanner and scene buttons, and a LED display indicator for easier navigation of controls and menu functions.



SCENEMAKER 1232

12 FIXTURES X 32 CHANNELS DMX INTELLIGENT LIGHTING CONTROLLER

PRODUCT DETAILS

KEY FEATURES

12 Fixtures with 32 DMX Channels each; 384 Channels in total

30 banks of 8 programmable scenes, 240 scenes total

6 chases of 240 programmed scenes from 30 bank

Executes multiple chases simultaneously

16 Sliders for direct control of channels

Auto Mode controlled by Speed and Fade Time

Master Blackout

Built-in microphone for Music triggering

USB LED Goose-neck Lamp INCLUDED

LED Display for easy navigation of menus

MIDI control over banks, chases and Blackout

Plastic end housing

SPECIFICATIONS

Power Supply	DC 9V-12V, 1000mA min.
USB Lamp	5V - 200 mA max
Protocols	DMX-512 USITT
Data Input	locking 3-pin XLR male socket
Data Output	locking 3-pin XLR female socket

SCENEMAKER 1232

12 FIXTURES X 32 CHANNELS DMX INTELLIGENT LIGHTING CONTROLLER

Data Pin Configuration

Pin 1 shield, Pin 2 (-), Pin 3 (+)

Controller Size (WxHxD)

520 x 73 x 183 mm

Net Weight 3.0 kg

Packing Dimension (WxHxD)

620 x 135 x 235 mm

Packing Gross Weight

3.7 kg