

MIOMIX 202UFX

4-CHANNEL PROFESSIONAL AUDIO MIXER WITH DIGITAL MULTI-EFFECT & UP TO 24-BIT/96KHZ USB I/O SOUNDCARD

MioMix 202UFX is a 4-channel mixer with digital multi-effect and USB soundcard ideal for small home recording, live gigs and podcasting applications that require professional quality level and maximum portability. Two Mic inputs are equipped with noise-less preamps that accept all main sound sources, such as condenser microphones - thanks to the +48V Phantom Power, dynamic mics, line and high-impedance inputs (guitars, basses, etc.). A stereo line input allows you to connect keyboards, CD players, DJ consoles, tablets, smartphones, etc. The 24-bit/48kHz digital effect with 16 commonly used presets (Hall/Room/Plate Reverb, Delay, Echo, Chorus, etc.) and TAP-Tempo function let you improve your performance and adjust up to two parameters of each effect. The USB 24-bit/96kHz Stereo In/Out Soundcard lets you connect to a computer and record or play top-quality audio files. An indispensable and reliable tool for all small audio applications.



MIOMIX 202UFX

4-CHANNEL PROFESSIONAL AUDIO MIXER WITH DIGITAL MULTI-EFFECT & UP TO 24-BIT/96KHZ USB I/O SOUNDCARD

PRODUCT DETAILS

KEY FEATURES

4 Total Channels

2 Mic/Line channels with noiseless preamp, combo connector, Hi-Z input for guitars, +48V Phantom Power, Peak Indicator

1 Stereo Line Channel with ¼" Jack inputs, +4/-10dB Pad Adapter and Peak Indicator

2-Band EQ for channels 1 and 2

24-bit/48kHz 16-Preset Digital Effect with TAP-Tempo and up to 2 adjustable Parameters

24-bit/96kHz USB I/O Stereo Soundcard with Playback Level Control

Headphone monitor out with level control

XLR Main Outputs with Master Level Control

Stereo 6-Led VU Meter Bar

Rugged and Lightweight Metal Case for Maximum Flexibility and Portability

240Vac - 5Vdc Power Adapter included

SPECIFICATIONS

Input Connections Balanced XLR/Jack Combo (Channel 1-2), Balanced ¼" Jack (Channel 3-4)

Output Connection Balanced XLR (Main Out L-R), Stereo ¼" Jack (Phones)

USB Connection Type-B, Female

Channel 1-2 Functions +48V Phantom Power, Impedance switch (Line/Hi-Z), 2-Band EQ (80Hz/12kHz +/-15dB) Effect Send Level, Pan Position, Channel Volume, Peak Led Indicator

MIOMIX 202UFX

4-CHANNEL PROFESSIONAL AUDIO MIXER WITH DIGITAL MULTI-EFFECT & UP TO 24-BIT/96KHZ USB I/O SOUNDCARD

| | |
|------------------------------|--|
| Channel 3-4 Functions | Impedance switch (+4/-10dB), 2-Band EQ (80Hz/12kHz +/-15dB), Effect Send Level, Pan Position, Channel Volume, Peak Led Indicator |
| USB I/O Soundcard | Up to 24-bit/96kHz Stereo Input/Output Streaming, USB Class-2.0 compliant |
| Digital Effect | 24-bit Sigma-Delta, 256-times oversampling, 48kHz sampling rate |
| Level Meter | 2x6 LED Meter |
| Max Output Level | 3 Vrms |
| Frequency Response | +/-0.5dB, 20Hz-20kHz |
| Dynamic Range | 102dB |
| THD+N @ 1kHz | =0.003% |
| Stereo Crosstalk | 92dB |
| Power Requirements | DC 5V, 1A |
| Power Consumption | Max. 2.5W |
| Power Adapter | 100-240Vac – 0.15A / 5Vcc – 1A Max (Power Adapter Included) |
| Size (WxDxH) | 166 x 165 x 66 mm |
| Packing Size (WxDxH) | 288 x 205 x 93 mm |
| Net Weight | 0.9kg |
| Gross Weight | 1.2kg |