


DJM-S9 PROFESSIONAL 2-CHANNEL BATTLE MIXER (BLACK)

Meet the DJM-S9, our first two-channel battle mixer for Serato DJ. The fully customisable Magvel Pro crossfader, tactile performance pads and FX buttons let you tailor the mixer according to your preferences. So get ready to decimate the dance floor with personalized FX and rigorous scratch performances. The DJM-S9 inherits its high-quality audio circuitry from our flagship 4-channel digital mixer, the DJM-2000NXS. The power inlet is designed to reduce resistance and deliver the stable sound you need in loud club environments.



DJM-S9

PROFESSIONAL 2-CHANNEL BATTLE MIXER (BLACK)

PRODUCT DETAILS

KEY FEATURES

The Magvel Fader Pro, magnetic crossfader ensures excellent operability, durability and response.

16 multi-colour touch pads give access to Hot Cue, Roll, Slice, Loop and more

Six customisable buttons on each side of the mixer, and two in the middle, trigger effects directly on your hardware

A high/low pass filter on each channel lets you manipulate FX by simply rotating the knob

Two large style levers that allow you to swiftly turn effects on and off

Two built-in USB soundcards

The MIC input features Echo FX and high-quality circuitry to eliminate unwanted distortion

Clip display

MIDI compatible

SPECIFICATIONS

Full assignable MIDI controls

Frequency Range 20 - 20,000 Hz

SN Ratio Line 107 dB

Distortion < 0.005 %

Power Requirements 100-240 V / 50/60 Hz

Serato HID Control

Auto Standby

Master Balance

DJM-S9

PROFESSIONAL 2-CHANNEL BATTLE MIXER (BLACK)

Level Meter Size	12 segment
ISO	3 band
ISO Range	-8 ~ +6 dB
Reverse Channels	
Level Meter Type	Shared Master
Peak Limiter	
Serato DJ FX powered by iZotope	55
3 Band Isolator	
Auto BPM Counter	
Crossfader Type	Magvel Fader Pro
Reverse crossfader and Tension Adjustment	
Mic Connection	XLR / Jack Combo
Talkover	ON/OFF Button and Talkover Attenuator
2 USB B ports	
Sample Rate	24 bit
Frequency	48 kHz
Inputs	2 CD/LINE (RCA), 2 PHONO (RCA), 1 MIC (XLR/Jack Combo), 1 AUX (RCA)
Outputs	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch Jack), 2 HEADPHONE MONITOR (1/4 inch Jack, MiniPin)
Software System Requirements	Windows 8.1/ 7(CPU) Core i3, i5 or i7 1.07 GHz Duo, (Memory) 4GB Mac OS X 10.10/10.9/10.8(CPU) Core i3, i5 or i7 1.07 GHz Duo, (Memory) 4GB
Display Resolution	1280 x 720 or higher
Dimensions (WxHxD)	267x107.9x407.3 mm
Weight	4.6 kg