


## DJM-S9 PROFESSIONAL 2-CHANNEL BATTLE MIXER (BLACK)

Meet the DJM-S9, our first two-channel battle mixer for Serato DJ. The fully customisable Magvel Pro crossfader, tactile performance pads and FX buttons let you tailor the mixer according to your preferences. So get ready to decimate the dance floor with personalized FX and rigorous scratch performances. The DJM-S9 inherits its high-quality audio circuitry from our flagship 4-channel digital mixer, the DJM-2000NXS. The power inlet is designed to reduce resistance and deliver the stable sound you need in loud club environments.



DJM-S9

# PROFESSIONAL 2-CHANNEL BATTLE MIXER (BLACK)

## PRODUCT DETAILS

### KEY FEATURES

The Magvel Fader Pro, magnetic crossfader ensures excellent operability, durability and response.

16 multi-colour touch pads give access to Hot Cue, Roll, Slice, Loop and more

Six customisable buttons on each side of the mixer, and two in the middle, trigger effects directly on your hardware

A high/low pass filter on each channel lets you manipulate FX by simply rotating the knob

Two large style levers that allow you to swiftly turn effects on and off

Two built-in USB soundcards

The MIC input features Echo FX and high-quality circuitry to eliminate unwanted distortion

Clip display

MIDI compatible

### SPECIFICATIONS

Full assignable MIDI controls

**Frequency Range** 20 - 20,000 Hz

**SN Ratio Line** 107 dB

**Distortion** < 0.005 %

**Power Requirements** 100-240 V / 50/60 Hz

Serato HID Control

Auto Standby

Master Balance

DJM-S9

# PROFESSIONAL 2-CHANNEL BATTLE MIXER (BLACK)

<b>Level Meter Size</b>	12 segment
<b>ISO</b>	3 band
<b>ISO Range</b>	-8 ~ +6 dB
Reverse Channels	
<b>Level Meter Type</b>	Shared Master
Peak Limiter	
<b>Serato DJ FX powered by iZotope</b>	55
3 Band Isolator	
Auto BPM Counter	
<b>Crossfader Type</b>	Magvel Fader Pro
Reverse crossfader and Tension Adjustment	
<b>Mic Connection</b>	XLR / Jack Combo
<b>Talkover</b>	ON/OFF Button and Talkover Attenuator
2 USB B ports	
<b>Sample Rate</b>	24 bit
<b>Frequency</b>	48 kHz
<b>Inputs</b>	2 CD/LINE (RCA), 2 PHONO (RCA), 1 MIC (XLR/Jack Combo), 1 AUX (RCA)
<b>Outputs</b>	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch Jack), 2 HEADPHONE MONITOR (1/4 inch Jack, MiniPin)
<b>Software System Requirements</b>	Windows 8.1/ 7(CPU) Core i3, i5 or i7 1.07 GHz Duo, (Memory) 4GB Mac OS X 10.10/10.9/10.8(CPU) Core i3, i5 or i7 1.07 GHz Duo, (Memory) 4GB
<b>Display Resolution</b>	1280 x 720 or higher
<b>Dimensions (WxHxD)</b>	267x107.9x407.3 mm
<b>Weight</b>	4.6 kg