

WF-V11PD

VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (209.8 MHZ)

WF-V11 is the answer to all those who need a reliable, high-quality sound, and easy to use wireless microphone system. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-V11 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.

WAR TOPIDund or type unknown

E457EPOAIOTOO PIJOOPE unknown

E457EnoAloT002160pe unknown





WF-V11PD

VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (209.8 MHZ)

PRODUCT DETAILS

KEY FEATURES

VHF Transmission with SMD Technology

4 available Frequencies in VHF Band

Simple user Interface for plug and play setup

30m ideal distance (without obstacles)

Strong yet lightweight bodypack transmitter

Professional and Lightweight Headset with high-sensibility dynamic cardioid capsule

SPECIFICATIONS

Carrier Frequency		VHF 200 - 215.3 MHz
Operating Frequency		209.8 MHz
Frequency Stabilization		Automatic calibration
Dynamic Range		> 90dB
Total Harmonic Distortion		< 0.5%
Frequency Response		40Hz - 16kHz / ±3dB
Packing Dimensions (WxHxD)		436 x 104 x 324 mm
Packing Gross Weight		2.0 kg
Receiver Power Supply	DC12V, 500mA	
Receiver Consumption	< 2W	
Signal/Noise Ratio	> 95dB	





WF-V11PD

VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (209.8 MHZ)

Receiving Sensitivity	10dBuV	
De-Emphasis	75uS	
Audio Output Level	Balanced 400mV; Unbalanced 400mV	
Receiver Size (WxHxD)	211 x 43 x 115 mm (antennas not incl.)	
Antenna Length	110 mm (min.) 430 mm (max.)	
Net Weight	0.295 kg	
Transmitter Power	10mW	
Modulation Type	FM	
Deviation	37KHz	
Battery Voltage	3V (2x1.5V AA-Type Batteries)	
Continuous Using	7 hours	
Pocket Trans. Dimensions (WxHxD)	62 x 103 x 30 mm	
Antenna (W/DxH)	Ø3 x 9 mm	
Pocket Transmitter Net Weight	0.132 kg (batteries included)	

